



## Soundcraft E8 Mixer

<b>Input Channels</b>	8 Mic/Line, mono 2 Line, stereo
<b>Aux. Sends</b>	2, globally selectable, pre/post
<b>Noise (22 Hz-22 kHz measurement bandwidth)</b>	
Mic EIN @ max gain, 150 $\Omega$ source impedance	-128 dBu
Mix @ max, faders down	<-85 dBu
<b>Crosstalk (typ. @ 1 kHz)</b>	
Channel mute	>96 dB
Fader cut-off (rel +10 mark)	>96 dB
Aux send pot offness	>86 dB
<b>Frequency Response</b>	
Mic/Line input to any output	+/- 0.5 dB 20 Hz - 20 kHz
<b>THD+ Noise</b>	
Mic gain 30 dB, -30 dBu input	
Mix out, fader max @ 1 kHz	<0.007%
<b>Input &amp; Output Impedance</b>	
Mic Input	2.4k $\Omega$
Line Input	11k $\Omega$
Stereo Input	100k $\Omega$
Outputs	75 $\Omega$
<b>Input &amp; Output Levels</b>	
Mic Input (max. level)	+17 dBu
Line Input (max. level)	>30 dBu
Stereo Input (max. level)	>30 dBu
Mix Input (max. level)	>20 dBu
Headphones (@200 $\Omega$ )	300mW
<b>Size</b>	
Weight	6.75 kg (14.88 lb)
Dimensions (HxWxD)	87.58 mm x 426.4 mm x 400.10 mm (3.45 in x 16.79 in x 16.33 in)
<b>Rack Mounting</b>	Requires Soundcraft Part#P-S20001D-01