

PLE-2CS Plena Two-zone Call Station

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Modern two-zone call station for the PLE series
- ▶ Selectable gain
- ▶ Speech filter and limiter
- ▶ Output level control
- ▶ Loop-through option for up to 8 call stations

The Plena two-zone call station is a modern, high-quality call station with a stable metal base design, a flexible microphone stem and a unidirectional condenser microphone. It can make calls to selected zones in a public address system built with the PLE series two-zone mixer and mixer amplifiers. In addition to tabletop use, the Plena design allows neat flush-mounting in desktops.

Functions

Gain, speech filter and intelligibility

This call station features selectable gain, a selectable speech filter, and a limiter for improved intelligibility.

Range

The call station has a balanced line level output, giving it a maximum range of 200 meters from the mixer, when using CAT-5 extension cables.

Loop-through

With the loop-through RJ-45 connector, it is possible to daisy chain multiple call stations.

Priority

The priority is automatic i.e. the call station nearest the mixer has priority and can override a call station further from the mixer. When a call is being made by a higher priority call station, a yellow light will display on the lower priority call stations.

Dip switches and status

DIP switches at the base of the call station select different microphone gain levels, chimes, and the speech filter. A service accessible rotary control provides microphone level attenuation. LEDs on the call station show which zones have been selected. An additional LED give visible feedback on the active state of the microphone and the system:

- Green flashing means standby (chime is sounding)
- Green indicates microphone active
- Amber indicates a higher priority call

Controls and indicators

- 2 x status LEDs
- PTT key
- 2 x zone selection keys
- 2 x zone selection LEDs
- DIP switches
- Rotary volume control

Interconnections

- 2 x RJ45 jacks

Certifications and approvals

Safety	acc. to EN 60065
Immunity	acc. to EN 55103-2
Emission	acc. to EN 55103-1

Region	Certification
Europe	CE

Parts included

Quantity	Components
1	PLE-2CS Plena two-zone call station
1	Cable terminated with a lockable CAT-5 connector

Technical specifications**Electrical**

Voltage range	24 VDC supplied by PLE mixer amplifier or mixer
Current consumption	<30 mA

Performance

Nominal sensitivity	85 dB SPL (gain preset 0 dB)
Nominal output level	700 mV
Input sound level (max)	110 dB SPL
Gain preset	-15 / 0 / +6 dB
Limiter threshold	2 V
Compression ratio limiter	1:20
Distortion	<0.6% (maximum input)
Input noise level (equiv.)	25 dB SPLA
Frequency response	100 Hz to 16 kHz
Speech filter	-3 dB at 315 Hz, high-pass, 6 dB/oct
Output impedance	200 ohm

Selections

Chimes	6
--------	---

Mechanical

Base dimensions (H x W x D) without microphone	40 x 100 x 235 mm (1.57 x 3.97 x 9.25 in)
Stem length with microphone	390 mm (15.35 in)
Cable length	5 m (16.4 ft)
Weight	Approx. 1 kg (2.2 lb)

Mounting	Standalone
Color	Charcoal with silver

Environmental

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

Ordering information**PLE-2CS Plena Two-zone Call Station**

Two zone call station with metal-base design, flexible microphone stem with unidirectional condenser microphone, two-zone selection.

Order number **PLE-2CS**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com