



CK99 L

CONDENSER LAVALIER MICROPHONE

HIDE AND SPEAK

for house-of-worship, conference and theater applications

The CK99 L is a condenser lavalier microphone with cardioid polar pattern. It provides a natural sound, with a slight rise above 10kHz for added clarity, perfect for applications in houses of worship, lectures and theaters.

Thanks to its small housing and the included durable metal clip, it can be inconspicuously and securely mounted on jackets and costumes. The CK99 L provides a professional three-pin mini XLR connector that fits the body pack transmitters of all AKG wireless microphone systems.

Cardioid polar pattern

eliminates noise from the rear

125° pickup angle

for inexperienced or very vivacious talkers

Small housing and durable metal clip

for inconspicuous, secure mounting




TECHNICAL SPECIFICATION

General	Audio frequency bandwidth	15 to 18000 Hz
	Equivalent Noise Level	34 dB-A
	Sensitivity	8.8 mV/Pa
	Signal to Noise	60 dB-A
	Electrical Impedance	200 Ohms
	Recommended Load Impedance	2000 Ohms

Polar Patterns

Cardioid



Powering Interface	Voltage	1.5 to 10 V
	Current	2 mA

Audio Output	Type	Mini XLR
	Gender	Female
	Contacts	3-pin

Design	Finish	matte black
---------------	--------	-------------

Dimensions / Weight	Height	23 mm
----------------------------	--------	-------